# **M@BIVIS@R**

## Android için KIOSK modunun Uygulanması

KIOSK modunun Android Enterprise Cihazlarına uygulanması için **Yönetici** Talimatları





### Hazırlık

Yönetici giriş bilgilerinizi kullanarak şirketinizin MDM domain'ine giriş yapın.



	Assignments	Android Only
oard	Policies	📞 Call Blacklists
	Assign Policies	Sirewall Rules
	Policy Restrictions	Keyguard Features
	T Criteria	Klosk Modes
	My Locations	<ul> <li>Permission Grant States</li> </ul>
	Policy Features	System Update Policies
	Access Point Names	iOS Only
	🐱 Exchange Configuratio	ns f Home Screen Layouts
	Predefined Apps	A iOS Accounts
	<ul> <li>Single App Modes</li> </ul>	N iOS App Notification Settin
	Violations	* Passcode Policies
al Device Count N	umber 🔛 Walpapers	Shared Device Configurati
34	Wifi Configurations	VPN Configurations
04		Web Content Filters

**Politikalar** menüsünde **Kiosk Modları**'nı seçin.





Adı	m 2	)										
config -	A Messages	• <u>\$</u> .∧	pplicatio	ns • (	Policies •	Use	rs ¥			A admin 1 O He,	sh	Şimdi " <b>Ekle</b> " butonuna tıklayın.
Allow Overview Button	a specific app of Allow Notifications	Allow System App Services	Allow Lock Screen	evice. Force Device Owner Kiosk	Allow Navigation Bar	Allow Task Manager	Allow Air Command Mode	Allow Air View Mode	Allow Edge Functions	Аррз		
				false	true	true	false	faise	false	com.boryazilim.android.bormdm.apj com.boryazilim.android.bormessagii com.hilti.mobile.channelcalculator com.hilti.mobile.ontrack3 com.android.dialer		
				true	true	true	faise	false	faise	com.boryazilim.android.bormdm.apj com.boryazilim.android.bormessagii com.whatsapp com.google.android.apps.maps com.Slack de.euregon.snapmda2.playstore com.boryazilim.android.borsecurevc com.android.dialer com.boryazilim.android.mobivisorfik com.google.Gmail		
				true	true	true	false	false	false	com.boryazilim.android.bormdm.apj com.android.vending		



BIVIS©R IC Commands ☐ Devices ♦ Config - ☎ Messages	<ul> <li>Applicatio</li> </ul>	ns • 🗊 Policies • 👤 Users • 🔺 admin 👤 💽 Hete	to Eng
III Kiosk Modes			
This lets you activate kiosk mode on Android device, in which only a specific app or	r apps can run on d	evice.	
Name (*)		Auto-Start Application:	
KIOSK Mode			~
		Apps: (Select apps that you want to add to Kiosk mode)	
Description		com.boryazilim.android.bormdm.app	
		com.boryazilim.android.bormessaging	
	h	com.boryazilim.android.borsecurevoip	
Kiosk Exit Password 👁 0		com.whatsapp	
		com.facebook.orca	
Minele Made Witte		com.google.android.talk	
Klosk Mode Title		com.facebook.katana	
O Que	ary Mappings	com.facebook.system	
Allans Status Bar		com.facebook.appmanager	
Allow Glauss Bar V		com.sec.enterprise.knox.express	
Allow Lock Screen ()		com sec android and shrowser	
		com concle android voutube	
		com.android.vending	
Device Owner Kiosk Specific Settings		com.android.contacts	
		□ com.android.settings	
Allow Overview Button ()		com.android.dialer	
		com.android.phone	
		C com accelo Omell	

Şimdi, **KIOSK mod**unun istenen adını girin ve Kiosk modunda görüntülenecek uygulamaların **paket adları**nı seçin.



	Application Shortcut Configurations	
	Application Shortcut Name (*)	
Samsung Specific Settings	Package Name (*)	
Force Device Owner Kiosk 0	Activity Details	
Allow Navigation Bar 0	O Add Shorteut	
Allow Multi Window Mode 0	Name Package Activity	
Allow Task Manager 0	There Are No Application Shortcuts Added Yet	Gerekli diger ayarları yapın.
		Ardından oluşturduğunuz
Allow Air Command Mode O		Kiosk modunu <b>kaydedin</b> .
Allow Air View Mode 0		
Allow Edge Functions 0		
× Cancel	H Save	



ad ad	Users -	Messages - Applications	iontig - 🔛	Devices \$20	SIVISUR IC Commands
	Android Only	Assignments			
+ Add Priv	Call Blacklists	Policies     Assign Policies			Manage Policies
for when to restrict or free that	<ul> <li>Keyguard Features</li> <li>Kiosk Modes</li> </ul>	Policy Restrictions	ature(Mobile hen the user	If rules when a device fr leatures are restricted w	Policies are used to define set assigned to users, their device
	<ul> <li>✓ Permission Grant States</li> <li>▲ System Update Policies</li> </ul>	My Locations     Policy Features			Q Policy Name
Actions	IOS Only Home Screen Layouts	<ul> <li>▲ Access Point Names</li> <li>▲ Exchange Configurations</li> </ul>	Features	Environment	Policy Name
Clone D Assign	<ul> <li>A IOS Accounts</li> <li>N IOS App Notification Settin</li> <li>Passcode Policies</li> </ul>	<ul> <li>Predefined Apps</li> <li>Single App Modes</li> <li>Violations</li> </ul>	Kiosk Mod	Android	Kiosk Richtlinie
Clone C Assign	<ul> <li>Shared Device Configurati</li> <li>VPN Configurations</li> <li>Web Content Filters</li> </ul>	Walpapers	Enabled Sy Compression	Android	xcall system apps
Clone CAssign	Always	w Popups	✓ Safari Allo	IOS	Pop-Ups erlauben
Clone 🛛 Assign	Always	ration List	Wifi Configu Elpro intern	Android	Elpro Test
Clone D Assign	Always	t Filter alphaview test	Web Conten	iOS	Test Webfilter Apple

Şimdi, menüde tüm **politikaların** bulunduğu "**Politikalar**" sekmesine geri dönün.



VISOR © Commands	Devices 🌣 🤇	Config - 🖾 Messages - 🙎 Applica	ations - 🗐 Policies - 💄 User	rs • 🔺 admin 1. O Help
Manage Policies				+ Add Privacy Policies - + New
licies are used to define set o signed to users, their device t	of rules when a device frequence of rules when a device frequency are restricted w	eature(Mobile Network, Camera, etc.) can be when the user meets at least one of the selec	used. Select device features and pre- ted criteria	saved criteria for when to restrict or free that device feature. When
Q Policy Name		,	Q Environment	×
			* * *	
olicy Name	Environment	Features	Criteria	Actions
losk Richtlinie	Android	Kiesk Mode Kieskmodus Android	Always	Cione 🛛 Assigned 🖉 Edit 💼 Delete
call system apps	Android	Enabled System Apps com.google.android.apps.ghotos	Always	Cione □ Assigned ≥ Edit  Delete
op-Ups erlauben	IOS	Safari Allow Popupa	Always	Cione 🗋 Assigned 🗡 Edit 箇 Delete
lpro Test	Android	Wifi Configuration List	Always	Cione 🗋 Assigned 🗡 Edit 💼 Delete
est Webfilter Apple	iOS	Web Content Filter alphaview test	Always	Cione 🛛 Assigned 🖉 Edit 💼 Delete
ISA	IOS	Passcode Policy GISA PW X Allow Password Auto Fill Allow Password Proximity Requests Writ Configuration Maxtent	Always	tiù Cione Ω Assigned ≥ Edit in Delete
tao aning	Android	Outooino Call Blacklist		Ciona D Assigned Z Eds Acates

Yeni bir politika ekleyin.

*Not:* Kiosk modunu mevcut bir politikaya da ekleyebilirsiniz. Bunu yapmak için, sadece **Düzenle**'yi seçin.

Geriye kalan adımlar aynı kalır.



OR	Commands	Devices	Config -	- 🖾 Me	essages -	£ A¢	pplications -	Policies -	LUsers -	*	admin 👤	O Help	(% Englis)
Canor							< Back	> Next					
							0%						
							Environmen	t(")					
					Android	iOS	Device Owne	r Work Profile (Andro	id)				
							Policy Nan	10					
OSK	Mode												
				© Cop	yright 2018	8 All rig	hts reserved	Developed by IO	FIQ GmbH.				

Cihazlarınız için yeni bir politika oluşturun.

Sadece iş amaçlı kullanılan cihazlar (COBO) için **Android'i** seçin.



Cancel			< Back > Next		
	50%				
Android & IOS & Device	Owner Work Profile (Android)				
				C Knox API Mapping 0	
Q KIOSK		×			
III Software Features					
Feature 0	11	Applicable Versions 0	Actions		
Kiosk Mode	CO-WP 1 1 0,	Samsung API	Kloskmodus Android	~ ×	
III Other					
Feature 0	11	Applicable Versions 0	Actions		
Kiosk Check Period	CO-WP 1 = 0,	Device Owner	C Unspecified		

Kısıtlanacak **özelliklerde**, Kiosk modu ayarlarını arayın ve yeni oluşturduğunuz **Kiosk modunu** seçin.

Ardından, daha ileri gitmek ve politikanızı kaydetmek için **ileri'ye** tıklayın.





Şimdi, **KIOSK modu politikasını** "Politikalar" öğesi aracılığıyla grubunuza ekleyebilirsiniz.

Bunu yapmak için, önce "**Kullanıcılar**" menüsüne gidin ve "**Gruplar**"ı seçin.



rice	es 🌣 Config 🗸 💈	Messages - Applications - Policies -	Users -	🔺 admin 🎗 💽 Help 🕅 Engli
			📿 Syn	chronize Ldsp Groups + Add
	×			
1	Users In Group	Applications	Policies	Actions
	6 Total 0 Administrator(s)	Adobe Acrobat Reader: PDF bearb Latest Version Cloudya Latest Version Notepad - einfache Notizen And 2 More	Roaming erlaubt / nicht erlaubt 🛛 😢	Cione Edit Delete
	3 Total 0 Administrator(s)	Secure Exchange Latest Version MobiVisor Messaging Latest Version MobiAdmin Latest Version And 5 More	No Policies	Cione ZEdit 🗎 Delete
	All Users 0 Administrator(s)	MobiVisor (>Latest Version)	No Policies	Clone 🗡 Edit 📋 Delete

Şimdi, KIOSK Modu'nu **uygulamak istediğiniz grubu** seçin.

Bunu yapmak için, grubun sağındaki "**Düzenle**"ye tıklayın.



AOBIVISOR	Commands	Devices OCor	nfig 🗸 🖾 Messages 🗸	Applications - Policies -	Users -
III Groups					
Q Sear	ch	×			
Group Type	Group Namel1	Users In Group	Applications		Policies
Local	Android Geräte	6 Total 0 Administrator(s)	Cloudya Cloudya Notepad - eint	t Reader: PDF bearb Latest Version 🔮 🍖	Roaming erlaubt
L Users Ⅲ A	pplications III W	lork Profile Applications	* Policies III Group	Administrators 🚔 Application Access Level	
Policy Name			Environment	Features	Criteria
KIOSK Mode			Android	Kiosk Mode Kioskmodus Android	Always
Kiosk Richtlinie			Android	Kiosk Mode Kioskmodus Android	

Şimdi "**Politikalar**" sekmesini seçin. Artık grubun politikalarını düzenleyebilirsiniz.



Applications		Policies	Actions
Adobe Acroba	at Reader: PDF bearb Latest Version 🗘 <table-cell></table-cell>	Roaming erlaubt / nicht erlaubt 😢	Clone 🖌 Edit 🗎 Delete
Environment	Features	Criteria	Add
Android	Kiosk Mode Kioskmodus Android	Always	+ Add
Android	Kiosk Mode Kioskmodus Android	Always	+ Add
Android	Enabled System Apps	Abunu	+ Add

KIOSK Modu'nu politikanıza eklemek için "**Ekle**"yi seçin.





Oluşturduğunuz KIOSK politikası, seçilen gruptaki "**Politikalar**" altında şimdi görüntülenmelidir.

**Kiosk modu**, artık gruptaki cihazlarda kurulmuş olmalıdır. Bu siteyi şimdi terk edebilirsiniz.



						IOS 12 01	IOS 17 🧧	IOS 18
				1.00				
						5.00		7.00
								1.00
					_			
						Inventory 0 De	wice Loca	tions C B
						Inventory VDe	The Loce	
7 Active O Servi Active	27 Inactive				ina	activity timeout	1	20 Minutes
7 Active 0 Send Active	27 Inactive				ina	intentory 00	1	20 Minutes
(7 Active) (3 Secret Active) X	Q User	×	. F Gro	up 👻 Android Gruppe	ina	inventory 00	1	20 Minutes
Addive () Second Addiver X	Q. User II Display Name	× Il Date	Enrolled	up - Android Gruppe	ina e 17	Model/Make	11	20 Minutes
Active Classification X Domment Android Enterprise	User     User     Display Name     Samsung Galaxy XCover6 P     Android Gruppe Q	<b>II</b> Date 10 180	F Gro Enrolled 9/2024 14:17	up - Android Gruppe	ina e 17	Model/Make samsung SM-G736B	12 11 14	20 Minutes
Android Enterprise	User     User     User     Samsung Galaxy XCover6 P     Avdroid Gruppe Q     Samsung Galaxy Tab     Android Gruppe Q	<b>II Date</b> 10 18/0 09/0	Frolied 9/2024 14:17	up • Android Gruppe II Last Connection Tim 20/11/2024 20:21 05/09/2024 18:55	ina e 17	Model/Make samsung SM-G736B samsung SM-X200	11 11 14 13	20 Minutes

Şimdi "**Cihazlar**" sekmesini seçin.

Bu sayfada, ilgili gruptaki tüm cihazları filtreleyebilirsiniz.



In Detailed Statistic	8							Inv
							_	
							Eq.	
Enrolled Devices	St Total 7 Active 0 Semi Active	(ar)	uc Ove					activ
III Enrolled Devices	SH Todal 7 Active 0 Servi Active		active					acto
Enrolled Devices	CLEASE (7 Active) (1 Seed Active		active)				in the	acto
Enrolled Devices     Q. Any	<b>ALES (1400)</b> (1000/4000) X	a	User		× P Group	Android Gruppe	-	acto
Enrolled Devices     Q Any	Ch Telan (? Astive) () Benel Active X	٩	uster		X P Group	Android Gruppe		activ
Q Any Actions 4 - 01	et Total (7 Active) (7 Sami Active X Devices are selected	٩	ucor		X P Group	Android Gruppe		acto
Enrolled Devices  Any  Actions 4 • 01  Select Filtered (3)	(4 Table (7 Antine) (4 Sand Antine X Devices are selected) Environment	Q 11	User Display Name	11	X P Group Date Enrolled II	Android Gruppe Last Connection Time	17	N
Enrolled Devices  Any  Actions 4 • 30  Select Filtered (3)	X      X	Q    	User Display Name Samsung Galaxy XCover6 Pro		x P* Group Date Enrolled II 18/09/2024 14:17	Android Gruppe Last Connection Time 20/11/2024 20:21	17	N
Enrolled Devices Q Any Actions 4 • • • • • • • • • • • • • • • • • •	X      X	Q 	User Display Name Samsung Galaxy XCover6 Pro IAndraid Grope G	11	X P Group Date Enrolled II 18/09/2024 14:17	Android Gruppe Last Connection Time 20/11/2024 20:21	17	N SI
Enrolled Devices Q Any Actions 4 - 30 Select Filtered (3)	Android Enterprise     Android Enterprise		User Display Name Samsung Galaxy XCover6 Pro Andreid Gruper G	11	X P Group Date Enrolled II 18/09/2024 14:17 09/04/2024 14:20	Android Gruppe Last Connection Time 20/11/2024 20:21 06/08/2024 18:55	17	N S
Enrolled Devices  Q. Any  Actions # • 01  Select Filtered (3)	K     K	Q	Display Name Samsung Galaxy XCover6 Pro Andreid Gruppe Cl. Kadevid Gruppe Cl.	11	X P Group Date Enrolled II 18/09/2024 14:17 09/04/2024 14:20	Android Gruppe  Last Connection Time 20/11/2024 20:21  06/08/2024 18:55	17	N SH
Enrolled Devices Q Any Actions 4 • • • •	Android Enterprise     Android Enterprise     Android Enterprise		Display Name Samsung Galaxy XCover6 Pro Andreid Gruppe G Samsung Galaxy Tab Andreid Gruppe G marketingbeam	11	X F Group Date Enrolled II 18/09/2024 14:17 09/04/2024 14:20 07/03/2024 14:00	Android Gruppe  Last Connection Time 20/11/2024 20:21 06/09/2024 18:55 11/03/2024 10:47	17	N SI
Enrolled Devices Q Any Actions 4 • • • • • • • • • • • • • • • • • •	Android Enterprise     Android Enterprise     Android Enterprise		User Display Name Samsung Galaxy XCover6 Pro Andreid Gruppe Q Andreid Gruppe Q Andreid Gruppe Q marketingbam Marketing (1 teer123 Q	11	X F Group Date Enrolled II 18/09/2024 14:17 09/04/2024 14:20 07/03/2024 14:00	Android Gruppe  Last Connection Time 20/11/2024 20:21  06/09/2024 18:55  11/03/2024 10:47	17	N 54

Bu grubun tüm cihazlarını seçin. "**İşlemler**" butonu görünecektir.

Q User Q Any × F Group - Android Actions 4 - 3 Devices are sele Debug Logs 11 Display Name 11 Date Enrolled 11 Last Conne Samsung Galaxy XCover6 Pro 18/09/2024 14:17 20/11/2024: Enforce Password Change Android Gruppe Q. Location Request Samsung Galaxy Tab 09/04/2024 14:20 06/09/2024 Android Gruppe Q. Reboot marketingteam 07/03/2024 14:00 11/03/2024 Marketing Q. test123 Q. Refresh Apps Android Gruppe Q. Refresh Klosk Mode Copyright 2018 All rights reserved Developed by IOTI Renew Session Status Request Update Policies Update Policies + Apps Delete from System

Buton bir menüye genişler. Bu menüden "**Update policies**" **İlkeleri** güncelle seçeneğini seçin. Bu işlemle birlikte, Kiosk Modu İlkesi tüm seçili cihazlara eşzamanlı olarak uygulanacaktır





Cihaz Sahibi (Device Owner) KIOSK modu artık cihaz üzerinde şu şekilde görünmektedir:

Yalnızca KIOSK modu için tanımlamış olduğunuz uygulamalar görüntülenir.

Bildirim çubuğunu devre dışı bıraktıysanız, bu çubuk da gizlenecektir.

#### KIOSK modu hakkında notlar:

- Samsung cihazlarda Samsung KIOSK modu da etkinleştirilebilir.
- Bir uygulamanın KIOSK modunda görüntülenebilmesi için öncelikle cihazda yüklü olması gerekir.
- Ayarlar ve benzeri sistem öğeleri KIOSK modunda devre dışı bırakılmaz yalnızca gizlenir.



#### Sorularınız var mı?

#### Yardımınıza mı ihtiyacınız var?

Sorun değil, ekibimiz size yardımcı olmaktan memnuniyet duyar.

**Bize şu numaradan ulaşabilirsiniz:** Tel: +49 341 991601 42

**Veya şu e-posta adresine yazabilirsiniz:** mds@iotiq.de